

MODEL NO .	MCP - 6
PRODUCT DESCRIPTION	6 - in - 1 multi - purpose hearing & transmission system
MULTI -PURPOSE RECEIVER	
Cordless operation type	VHF (87.50 Mhz)
FM radio type	Auto Scan with reset (88 - 108 Mhz)
Sound magnification type	Omni - directional, 48db gain
CORDLESS/FM or MAGNIFIER selector	Yes
Personal volume control	Yes
Power ON/OFF switch	Yes
LED power ON/OFF indicator	Yes
Detachable belt - clip	Yes, included
Detachable stereo earphones	Yes, included
Bsttery requirement	2 x AAA/LR03/UM4 (not included)
Earphone size & type	2 x 15mm mylar, 32 Ohm, included
Weight (without battery)<approx.>	80 gms
AUDIO TRANSMITTER	
Portable application	Yes
Detachable belt - clip	Yes, included
Power requirement(battery)	1 x 9v (not included)
Optional power requirement (AC/DC adaptor)	4.5v 50mA (not included)
Power ON/OFF switch	Yes
LED power ON/OFF indicator	Yes
Condenser microphone input	Yes
AUDIO / MIC selector	Yes
Audio cord with 3.5mm plug	Yes, attached
Therefore transmission antenna	PCB built - in
Weight (without AC/DC adaptor)<approx.>	140 gms
Transmission frequency	VHF (87.50 Mhz)
STANDARD ACCESSORIES	
3.5mm - 6.3mm plug adaptor	Yes
3.5mm - RCA plug adaptor	Yes
Condenser microphone unit	Yes
Stick - on bracket for microphone unit	Yes
Beit clip for transmitter	Yes
Tie clip for microphone	Yes
English & Spanish instruction manual	Yes
GIFT BOX INFORMATION	
Gift box	Full colored
Inner protection	Polyfoam
Dimension<approx.>	19.7 x 15.2 x 7.7(cm)
Weight<approx.>	350 gms
EXPORT CARTON INFORMATION:	
No.of sets per export carton	30
Export carton dimension <approx.>	64 x 44 x 35 (cm)
Net weight <approx.>	10.5 kgs
Gross weight <approx.>	12 kgs
CBM <approx.>	0.099
AVAILABLE OPTIONS(extra charge):	
Extra receiver	HFM - 02
AC/DC adaptor (4.5v 50mA)	Yes
Replacement earphones	Yes
Display stand	Yes
Batteries	Yes